

GPS PERSONAL TRACKER



**Help And Protection
For You And Your Family**

GT02

Summary & Features



GPS Personal tracker GT02

GT02 is a GPS/GSM/GPRS Personal tracking device which is specially developed and designed for children, elders and pets real-time tracking and security.

GT02 represents the perfect combination of GSM and GPS technologies. With sophisticated techniques, GT02 is the typical design for communications and GPS service. Built in back up battery, it can work continuously for 6 hours, and support standby time around 3-4 days. LCD display show location info in real-time. With built-in instant surge power adoption, it can protect inside components.



**HELP AND PROTECTION
FOR YOU & YOUR FAMILY**

Features:

1. Tracking Via SMS or GPRS (TCP/UDP)
2. Track on command or by time interval
3. With LCD display to show location info
4. Two ways communication
5. Geo-fence alert
6. SOS panic button, emergency alert
7. low battery alert
8. Voice monitoring
9. 3 buttons for making call and/or sending SMS



Installation & Usage

Hardware and Accessories



- ① Answer button
- ② Call 1 Button
- ③ SOS Button
- ④ Call 2 Button
- ⑤ Call 3 Button
- ⑥ Power status LED light
- ⑦ Switch
- ⑧ USB Port
- ⑨ MIC
- ⑩ Louder Speaker



Installation Process

SIM Card Installation

Check that the SIM card does not run out of credit (test the SIM card in a phone to make sure it can send and receive SMS). Check that the SIM card has opened GPRS function. Check that the SIM card lock code is turned off. Charge the battery for at least 5 hours in power-off status using the wall charger. Press and hold the switch, wait for about 20 seconds. It will then enter standby mode. It is suggested that you be in an outer place where it can receive better GPS when you turn on the device.



Status Indication

Status Indication

Buttons: there are 6 buttons in the tracker with different functions.



- ① Answer Button: Press : answer the call when on call; switch between time interface and setting menu. Press and hold: enter main interface.



- ② Call 1 Button: in setting menu, press call 1 button, confirm the selection. Press and hold: make a call to preset phone number 1.
- ③ SOS Button: press and hold, SOS alert active, tracker will make a call to 3 preset phone numbers and send sms to authorized phone number.
- ④ Call 2 Button: Press and hold: make a call to preset phone number 2.
- ⑤ Call 3 Button: press and hold, make a call to preset phone number 3.



How it works



How it works



1. Users with tracker get current location information from satellite.
2. tracker will run the program and transfer location information to GPRS data.
3. Tracker sends the GPRS data to Data center via GSM/GPRS network.
4. Data center will operate all data from tracker, and make it show up in the tracking platform, or send commands to the tracker accordingly.
5. You can check current location and do the tracking by smart phone, PC, PAD and so on.

Commands List



How to get realtime location

Live location report 6660000

send command: 6660000 to tracker, it replies text message as followed format:
you can enter the coordinate in Google map to get the current location.



Lat:+2309.7604 Long:+11318.6745 Speed:
4.78km/h Direction:67 Date: 2012-6-4
Time:08:12:42 BS:284F83BB FIX:A
TATE:SMS(23.16267, 113.31124)

User can also get live location information (include: date, time, coordinate, speed, contact person, contact phone number, current location address) through online tracking platform



Alert setting

Authorized Phone Number for Alerts #710#phone number#0000##

Remarks: To authorize phone number for all alerts sms, which include sos alert, geofencing, low battery alert and so on. Phone number Max.16 digits

I.E: #710#2745884712#0000##